

AUDIO/VISUAL CONNECTOR KIT AV-CK

INTRODUCING THE NEW AUDIO/VISUAL CONNECTOR KIT



Federal Signal's new audio/visual connector kit is now available to order. The connector kit can be used to attach a variety of Federal Signal audible and visual products together to create a combination unit.

Connector kit AV-CK includes one 1/2-inch NPT offset conduit nipple and two silicone washers. The table on the next page shows all the audible/visual combinations that are possible to create using the AV-CK. Please note that some combinations require drilling. (These products are denoted with an asterisk.) Products that do not require drilling have 1/2-inch NPT threaded opening to fit the connector.

Installation requires the user to fit washers and twist the conduit nipple into the audible and visual product. The silicone washers should be placed over both sides of the conduit nipple and up against both the audible and visual product to ensure that no moisture or dust gets into either product. Only the audible product needs to be mounted. Supply one power circuit for combination audible and visual signal activation. Supply two separate power circuits to independently control the audible and visual signal activation.



AV-CK



Combination Unit Example:
50GC, UTM, WB, FB2LED, and AV-CK

HOW TO ORDER

MODEL	DESCRIPTION	UPC CODE
AV-CK	Audio/Visual Connector Kit	782979253570
OPTIONAL ACCESSORY		
KIT-WBTB	Kit, terminal block connector for WB or LHWB	782979230601

TIMING

The AV-CK connector kit is available to order today.


COMBINATIONS

SAFE AREA						
STEP 1: CHOOSE VOLTAGE	12/24 VDC		24 VAC	120 VAC		240 VAC
STEP 2: CHOOSE AUDIBLE OPTION	50GC-024BG** + WB + UTM	450E + WB-NM	50GC-024BG + WB + UTM	50GC-120BG + WB + UTM	350WB-120	350WB-240
STEP 3: CHOOSE VISUAL OPTION	SLM300+ SLMBD-012-024GY*		SLM300+ SLMBD-012-024GY*	SLM300+ SLMBD-120-240GY*		SLM300+ SLMBD-120-240GY*
	SLM350+ SLMBD-012-024GY*		SLM350+ SLMBD-012-024GY*	SLM350+ SLMBD-120-240GY*		SLM350+ SLMBD-120-240GY*
	SLM100+ SLMBP-012-024GY		SLM100+ SLMBP-012-024GY	SLM100+ SLMBP-120-240GY		SLM100+ SLMBP-120-240GY
	SLM200+ SLMBP-012-024GY		SLM200+ SLMBP-012-024GY	SLM200+ SLMBP-120-240GY		SLM200+ SLMBP-120-240GY
	FB2PST-012-024			FB2PST-120		FB2PST-240
	FB2LED-012-024			FB2LED-120-240		FB2LED-120-240
	FB2LED-QC-012-024			FB2LED-QC-120-240		FB2LED-QC-120-240
	LP3P-012-048			LP3P-120		LP3P-240
	LP3PL-024**			LP3PL-120		
STEP4: ADD ADAPTER KIT	AV-CK					


*Requires drilling and customer supplied 1/2-inch NPT locknut

**24VDC only



HAZARDOUS LOCATION			
STEP 1: CHOOSE VOLTAGE	12/24 VDC	120 VAC	240 VAC
STEP 2: CHOOSE AUDIBLE OPTION	450EWBX-024	350WBX-120	350WBX-240
STEP 3: CHOOSE VISUAL OPTION	FB2LEDX-012-024	FB2LEDX-120-240	FB2LEDX-120-240
	FB2LEDX-QC-012-024	FB2LEDX-QC-120-240	FB2LEDX-QC-120-240
STEP4: ADD ADAPTER KIT	AV-CK		



350WBX + FB2LEDX + AV-CK



350WB + SLM100 + SLMBP + AV-CK



350WB + SLM300 + SLMBD + AV-CK

